

22


 Europäisches
 Patentamt

European
 Patent Office

Office européen
 des brevets

EP00/1119

E 2 U



Bescheinigung

Certificate

Attestation

Die angehefteten Unterla-
 gen stimmen mit der
 ursprünglich eingereichten
 Fassung der auf dem näch-
 sten Blatt bezeichneten
 europäischen Patentanmel-
 dung überein.

The attached documents
 are exact copies of the
 European patent application
 described on the following
 page, as originally filed.

Les documents fixés à
 cette attestation sont
 conformes à la version
 initialement déposée de
 la demande de brevet
 européen spécifiée à la
 page suivante.

Patentanmeldung Nr. Patent application No. Demande de brevet n°

99200525.6

PRIORITY DOCUMENT
 SUBMITTED OR TRANSMITTED IN
 COMPLIANCE WITH
 RULE 17.1(a) OR (b)

Der Präsident des Europäischen Patentamts:
 Im Auftrag

For the President of the European Patent Office

Le Président de l'Office européen des brevets
 p.o.



I.L.C. HATTEN-HECKMAN

DEN HAAG, DEN
 THE HAGUE,
 LA HAYE, LE

03/04/00

THIS PAGE BLANK (USPTO)



Europäisches
Patentamt

European
Patent Office

Office européen
des brevets

Blatt 2 der Bescheinigung
Sheet 2 of the certificate
Page 2 de l'attestation

Anmeldung Nr.:
Application no.:
Demande n°: 99200525.6

Anmeldetag:
Date of filing: 26/05/99
Date de dépôt:

Anmelder:
Applicant(s):
Demandeur(s):
Mannesmann VDO Aktiengesellschaft
60388 Frankfurt am Main
GERMANY

Bezeichnung der Erfindung:
Title of the invention:
Titre de l'invention:
Method for selection of a tuning frequency

In Anspruch genommene Priorität(en) / Priority(ies) claimed / Priorité(s) revendiquée(s)

Staat:
State:
Pays:

Tag:
Date:
Date:

Aktenzeichen:
File no.
Numéro de dépôt:

Internationale Patentklassifikation:
International Patent classification:
Classification internationale des brevets:
H03J1/00, H03J7/18

Am Anmeldetag benannte Vertragsstaaten:
Contracting states designated at date of filing: AT/BE/CH/CY/DE/DK/ES/FI/FR/GB/GR/IE/IT/LI/LU/MC/NL/PT/SE
Etats contractants désignés lors du dépôt:

Bemerkungen:
Remarks:
Remarques:

The original title of the application reads as follows:
Method for selection of a receiver tuning frequency

THIS PAGE BLANK (USPTO)

Method for selection of a receiver ⁽⁶³⁾tuning frequency

The invention relates to a method for selecting a tuning frequency for receiving an RF transmitter within an RF frequency band and an FM receiver executing the method.

An FM receiver executing the above method is on itself known e.g. from European Patent 0 333 194. The known FM receiver complies with the FM RDS broadcasting standard as defined in 'Specification of the Radio Data System FM RDS for VHF-FM Sound Broadcasting' by the European Broadcasting Union (EBU), EBU document Tech 3244-E, March 1984 and updated in the subsequent revisions thereof. Reference is made to this document for a correct understanding of the meaning and definition of the various terms used hereinafter in connection with the FM RDS standard.

The cited FM receiver comprises a first or stationary tuner circuit and a second or scanning tuner circuit. The stationary tuner circuit is used to tune the receiver to a broadcast transmitter station with a wanted audio program, hereinafter indicated as first transmitter frequency, and to process the audio program signals for sound reproduction. If the transmitter transmits RDS data as well, then the stationary tuner circuit will also extract the RDS data carried by the received RDS transmitter signal, in particular a list of alternative frequencies (AFs). Such list provides tuning data of transmitters carrying the same program as the one the stationary tuner circuit is actually tuned to. The scanning tuner circuit is used to monitor the reception quality of the transmitter signals at each of those AFs. For this, the scanning tuner circuit is sequentially switched to each AF in the AF list to measure the fieldstrength of the transmitter signals at the respective AFs. The fieldstrength information is stored in a memory and repeatedly updated in sequential scan cycles. On deterioration of the received stationary transmitter signal, hereinafter indicated as first transmitter frequency, the

stationary tuner circuit is automatically switched over in its tuning from said first transmitter frequency to another transmitter frequency, hereinafter indicated as second transmitter frequency. In the known receiver, the AF stored
5 in the memory having highest fieldstrength is chosen to be such second transmitter frequency. However, the reception quality measurement is based on the momentary fieldstrength of the RF FM reception signal and the AF having highest fieldstrength at the moment of tuning switch over may lose
10 this position very quickly, due to fluctuations in the environmental reception conditions. This may cause instabilities in the tuning of the receiver. Furthermore, in this known receiver, the selection of a second transmitter frequency is limited to the AFs included in the RDS AF list,
15 being alternative frequencies carrying the same audio program as the first transmitter frequency.

An object of the invention is to improve the tuning behaviour of the above mentioned receiver.

To this end, a method for selecting a tuning frequency
20 for receiving an RF transmitter within an RF frequency band is characterized by a band scanning search for detecting transmitters exceeding a predetermined reception quality level, by storing the tuning data thereof and allocating thereto a permanency factor indicating the permanency in
25 reception quality thereof, said tuning frequency being selected on the basis of at least said permanency factor.

An FM receiver executing the method according to the invention comprising first and second tuner circuits
30 respectively for receiving a first FM transmitter and for detecting in an FM band FM transmitters received with a reception quality exceeding a predetermined quality threshold level, and storage means for storing the tuning data of the so detected FM transmitters, the first tuner
35 circuit switching over from an actually received first FM transmitter to a second FM transmitter selected from the

detected FM transmitters when the reception quality of the first FM transmitter decreases below a predetermined level, is therefore characterized by a processing unit allocating to each detected FM transmitter a permanency factor
5 indicating the permanency in reception quality thereof, said selection of the second FM transmitter being based on at least said permanency factor.

By the measure according to the invention the criteria for selecting a second transmitter are not only based on the
10 reception quality or fieldstrength thereof, but also on the duration or permanency of the reception quality. The longer the reception quality is in excess of said predetermined minimum level, the more reliable and stable the reception of the transmitter signal in question is. By tuning the
15 stationary tuner circuit to such a transmitter, the tuning behaviour of the stationary tuner will be stabilised.

To allow easy implementation, the method is preferably characterized in that the band scanning search is being repeated in subsequent scan cycles, each detected
20 transmitter increasing respectively decreasing in permanency factor dependent on the detection respectively the absence of detection thereof in subsequent scan cycles.

An FM receiver executing said preferred method is characterized by tuning control means controlling the tuning
25 of the second tuning circuit to repeat the band scanning search in subsequent scan cycles, the processing unit increasing, respectively decreasing, stepwise the permanency factor of a transmitter at each detection, respectively in the absence of detection, thereof in a subsequent scan
30 cycle.

In a further preferred method the tuning data of transmitters having a permanency factor decreasing below a predetermined permanency threshold level are being erased to
exclude such transmitters from being selected.

35 An FM RDS receiver executing said preferred method is characterized in that the storage locations of tuning data

relating to transmitters decreasing in permanency factor below a predetermined permanency threshold level, being released for storage of other transmitter data.

5 This measure further improves the efficiency in the use of memory capacity without losing the information which transmitter frequency should be chosen in case the actually received transmitter signal decreases below said predetermined threshold level.

10 Furthermore, the band scanning search will reveal all transmitters in the FM band meeting the minimum reception quality requirement. This allows to apply said selection of the second transmitter frequency also when changes in the audio program are permitted or wanted. Dependent on the user's choice, such second transmitter frequency may carry
15 an audio program signal different from the actually received one, but falling e.g. within the same PTY category, and/or including traffic messages. The selection is therewith PTY determined. RDS program codes may be used for the identification of such audio programs.

20

In an FM receiver capable of receiving RDS signals implementing such selection the processing unit repeatedly monitors the permanency factor of the FM transmitters carrying an audio program within the same PTY category as
25 the audio program of the first FM transmitter.

In another preferred method according to the invention the second transmitter is selected from FM transmitters carrying traffic messages on the basis of fieldstrength in addition to the permanency factor.

30

In an FM receiver capable of receiving RDS signals executing this method the processing unit operates to monitor the permanency factor of FM transmitters carrying traffic message information as well as the fieldstrength thereof, the second FM transmitter being selected from the
35 detected FM transmitters upon receiving a traffic

announcement signal on the basis of fieldstrength in addition to the permanency factor.

The fieldstrength is used in this measure to identify the nearest transmitter sending traffic messages, which are most relevant to the actual location of the user because of the proximity of the transmitter.

These and further aspects and advantages of the invention will be discussed in more detail hereinafter with reference to the disclosure of preferred embodiments, and in particular with reference to the appended Figures that show:

Figure 1 a blockdiagram of a dual tuner FM RDS receiver according to the invention;

Figure 2 an organisational scheme of the list of transmitter related data as stored in the FM RDS receiver of Figure 1;

Figure 3 a flowchart illustrating the method according to the invention as being executed by the FM RDS receiver of Figure 1.

Figure 1 shows a blockdiagram of an FM receiver according to the invention, which in the preferred embodiment as shown complies with the FM RDS broadcasting standard as defined in above cited EBU document. Reference is made to this document for detailed information on the meaning and definition of the various terms and abbreviations relating to the RDS standard, as mentioned hereinafter.

The FM receiver receives RF FM signals through an antenna 1 and following this antenna 1, it comprises first and second tuner circuits 2 and 3, the tuning frequency thereof being controlled from tuning control means 10, 11, 25. The tuning control means 10, 11, 25 comprise a central processing unit (CPU) 25 and an I/O control module 11 being included in a microprocessor 12 and connected through a control bus 10 to the first and second tuner circuits 2 and

3. By manual operation of one of keys 21-24 the tuning frequency of the first tuner circuit 2 can be set through a user interface I/O module 20 to the transmitter frequency of a wanted FM broadcast station. Key 21 is to activate an autostore functionality, key 22 is to activate an up/down search, key 23 is to switch on/off the reception of traffic messages and key 24 is to activate a search for programs within the same PTY category as the one actually received. These functionalities require the use of a program memory 26 for the storage of program software and a timer module 28 and are on themselves already known from e.g. the FM RDS radio receiver type VDO RC 959 RDS. The first tuner circuit 2 provides for the stationary selection and demodulation of a wanted RF FM broadcast signal into baseband and comprises means to measure the reception quality of the received FM RF signal. A quality factor reflecting said reception quality is supplied via a quality level line 14 to an AD converter module 15 of the microprocessor 12 to be further processed as described hereinafter.

Dependent on the content of the received FM broadcast signals, the baseband FM modulation signal may comprise an RDS signal and/or a mono or stereomultiplex signals. This baseband signal is supplied via a signal line 5 from an output of the first tuner circuit 2 to a digital signal processor 6. The digital signal processor 6 comprises audio signal processing means (not shown) to process mono audio signals and eventually demultiplex stereomultiplex signals into stereo left and right audio signals. These stereo left and right audio signals are supplied to an audio amplifier 8 and subsequently to a stereo loudspeaker set 9 for respectively amplification and reproduction thereof.

The digital signal processor 6 is coupled to an RDS decoder 7 to decode RDS data contained in the received FM broadcast signal. The decoded RDS data are supplied via an RDS data line 18 to an RDS data I/O module 19 of the

microprocessor 12. RDS data processing occurs under control of the CPU 25 of the microprocessor 12.

The tuning frequency of the second tuner circuit 3 is automatically varied by the tuning control means 10, 11, 25 to scan over the full RF FM broadcast reception band ranging from 87.5 MHz to 108 MHz, starting from e.g. the lower end of said RF FM band. The scanning operation will be interrupted upon first reception of an FM broadcast station fx having a signal reception quality exceeding a certain predetermined threshold level qt (hereinafter also indicated as scan hit). During an interruption interval, measurement, processing and storage steps are being made under control of the CPU 25, as described in the following with reference to Figure 2.

1. the tuning data of fx is stored at a storage address Tx of a data memory 27 of the microcontroller 12;

2. a permanency factor px is being allocated to fx, set at unity value and stored at Tx;

3. the actual reception fieldstrength is measured and a fieldstrength factor sx reflecting said reception fieldstrength is stored at Tx;

An RDS decoder 4 following the output of the second tuner circuit 3 is to extract RDS data from the demodulated RDS signal, if fx is carrying such RDS data. The RDS data is supplied via an RDS data line 16 to an RDS data I/O module 17 of the microprocessor 12 and the various program related RDS codes included therein, such as e.g. the PTY-, TA-, TMC-, PS-, and/or PS Mask codes, are stored in said data memory at the storage address Tx of fx. Eventually an RDS flag NW identifying RDS transmitters with value 1 and non-RDS transmitters with value 0 may be stored in TX as well.

After these steps have been completed for fx, the scanning is resumed until it is interrupted again, when the next FM broadcast station fy in the RF FM broadcast reception band having a signal reception quality exceeding

qt is detected. The above measurement, processing and storage steps are repeated for fy, the tuning data thereof, as well as a permanency factor py and a fieldstrength factor sy, eventually along with RDS program data are being stored in the data memory at storage address Ty. These steps are repeated for each such FM broadcast station until the full RF FM broadcast reception band has been scanned, whereafter the scanning operation is repeated, either in the same or in reversed scan direction.

The reception quality may be based on one or more parameters, such as e.g. the reception fieldstrength, the (lack of) multipath and other environmental sources of pollution. The above predetermined threshold level qt is chosen such, that RF FM broadcast signals exceeding this level can be processed properly without giving rise to receiver malfunctioning and/or noticeable signal distortions.

For a practical implementation of the detection of FM broadcast stations having a signal reception quality exceeding a certain predetermined threshold level qt, reference is made to above cited car radio receiver type VDO RC 959 RDS, where a similar feature is used under its so-called autostore functionality. Said known receiver also provides a reference for the measuring of the actual reception fieldstrength of certain transmitters and the storage of a fieldstrength factor sx reflecting said reception fieldstrength, the retrieval of various program related RDS codes included in the received RF FM signal, such as e.g. the PTY, TA-, TMC-, PS-, and/or PS Mask codes and the storage of these data in a data memory at storage addresses related to the relevant transmitter frequencies. The known receiver is based on a single tuner concept and provides said functionalities during short muting intervals in the reproduction of the main audio program being limited to AFs only, i.e. transmitter frequencies carrying the same audio program as the stationary received one.

If in a subsequent scan operation fx is detected again, which means that the reception quality of fx still exceeds the predetermined threshold level qt, then the permanency factor px is incremented with unity value, thus resulting in
5 px=2. A maximum to the permanency factor can be set, e.g. at three, which means that any scan hits on fx following up to the third one in a row will have no effect on this maximum value of px=3.

If after a scan hit, fx fails to appear in a subsequent
10 scan (hereinafter also indicated as an empty scan), then px will decrement with unity value, each time a subsequent scan appears to be empty on fx. The minimum value of px is set at px=0, which is obtained in at most three empty scans in a row. Any empty scan following the third one in a row, will
15 have no effect on this minimum value of px=0. If px decreases below a permanency threshold level, which in this receiver is set at px=1 (unity), then all data in the data memory at the storage address Tx of fx will be removed. This removal of data is in practise effected by releasing the
20 relevant storage locations for the storage of new data.

As long as px differs from zero, the last measured fieldstrength factor sx is stored at the storage address Tx of fx, while overwriting the prior one.

In contrast with said known receiver, the second tuner
25 circuit 3 of the FM receiver according to the invention collects not only transmitter data of AFs only, but of all transmitters exceeding the predetermined reception quality level qt. This allows to offer the user a broader range of options in automatically selecting audio programs.

30 For instance, by activating the 'autostore' option with key 21, the fieldstrength factor of the various transmitters stored in the data memory may be compared with a certain threshold level, chosen such that it is exceeded by only a limited number of transmitters (e.g. 10), which can be RDS-
35 or non-RDS transmitters. The tuning data of these transmitters are stored in the autostore memory and called

up by touching the key 21. According to the invention the threshold level may be based on a predetermined threshold value for the permanency factor, eventually in combination with a predetermined threshold value for the fieldstrength factor.

5 This also applies to the threshold level for use in the up/down search of transmitters, which feature can be activated with key 22.

The various program related RDS codes like PTY, TP and TA are used to offer the user options in automatically selecting within the category of programs indicated therewith, the best receivable transmitter from those having these codes stored in the data memory of the receiver. The availability of the tuning data of all receivable transmitters in the data memory of the receiver, together with the permanency factor and the fieldstrength factor thereof allow to immediately identify within a certain RDS program category, which in terms of these factors is the best to receive transmitter.

A switching of the tuning of the first tuner circuit 2 to the best to receive transmitter carrying a program within the same PTY category as the one the first tuner is actually tuned to, is activated with key 24.

By an operation of key 23, the receiver can be set to reproduce traffic messages. In accordance with the invention, the criterium to select an appropriate traffic message transmitting RDS broadcast station amongst those carrying the traffic announcement flag is based on the permanency factor, i.e. the best to receive RDS traffic message broadcast station having the highest permanency factor. If the highest permanency factor is shared by various transmitters, then the fieldstrength factor may additionally be used to come to the one best to receive. The transmitter received strongest (i.e. with highest fieldstrength) is in practice nearest to the receiver location and the traffic messages of that transmitter are therewith most relevant to the user.

Figure 3 shows a flowchart of an algorithm for collecting and updating transmitter and RDS program related data to be used in a method for tuning the reception of radio broadcast signals to an FM transmitter in accordance with the invention, in which steps a1-a15 have the following meaning:

a1 Switching on the radio and starting the method according to the invention.

for selecting a tuning frequency for receiving an RF FM transmitter within an RF FM frequency band

a2 The second tuner circuit 3 is initialised for starting a scan cycle from the lower end of the FM frequency band at 87.5 MHz. The data memory 27 is initialised for transmitter and RDS program related data storage .

a3 The tuning frequency of the second tuner circuit 3 is being increased to scan the FM and interrupted upon reception of a transmitter fx. During an interruption period the signal reception quality (this can be the fieldstrength or other parameters defining the reception quality level) of fx is measured. In the following the fieldstrength is taken as a measure for the reception quality. Store a fieldstrength factor sx reflecting the fieldstrength of fx at a storage address Tx of the data memory 27.

a4 If the fieldstrength factor sx exceeds the threshold level qt then go to a9. Otherwise go to a5.

a5 The fieldstrength factor sx is not good enough. Check now the permanency factor px of fx. If this px is not equal to zero (which means fx has been detected in at least the preceding scan), then goto a6. If px=0 then goto a7.

a6 Decrement px with unity value.

a7 px=0: clear all data from the storage address Tx of the data memory 27.

a8. Resume the scanning operation. If the end of the FM band (108,0 MHz) is reached, go to a3 to start a subsequent scan cycle, starting again from the lower end of the FM band (87.5 MHz).

5 a9 The fieldstrength factor sx exceeds qt. Wait some time to check whether fx carries RDS information.

 a10 Is the PI code received. If so, go to a11, otherwise go to a 12.

 a11 Set the RDS flag NW at 1 and store all RDS data at Tx of data memory 27.

 a12 Check the RDS flag NW at Tx. If NW=1, go to a13, otherwise go to a14.

 a13 Clear the RDS flag by setting NW to 0.

 a14 Clear all RDS data at Tx

15 a15 The reception quality was OK. Increment px with unity value (until maximum at px=3 has been reached).

The data memory 27 therewith contains at any time the most recent status of the receivable transmitters in the FM band in terms of momentary reception quality or fieldstrength sx and permanency or stability of reception quality px. The continuous availability of the abovementioned transmitter related data in an FM receiver according to the invention allows to determine immediately which transmitter within the FM band provides optimal reception conditions, i.e. which transmitter within the FM band has highest permanency factor px. If the highest px value is shared by several transmitters, then the fieldstrength factor sx may be taken additionally to determine the best to receive transmitter. The availability of program related RDS data allows to restrict the group of transmitters to be considered for the above determination of the best to receive transmitter. If, for instance, the user is only interested in hearing a specific audio program with optimal quality, then in accordance with the invention it

should be determined, which transmitter having the PI code identifying said specific audio program has highest permanency factor px amongst those detected within the FM band. Similarly, the group of transmitters to be considered
5 for the above determination in case the user is interested in any audio program within a certain PTY category, is limited to those transmitter carrying the RDS PTY code of said category. Accordingly, in determining the best to receive traffic message broadcast transmitter station, use
10 can be made of the RDS TA code to limit the group of transmitters to be considered therefor.

The invention is not restricted to the embodiments described above and may well be used in e.g. a non-RDS receiver for implementing an 'autostore' functionality,
15 wherein a number of strongest transmitters are being stored under a same number of tuner preselection keys. Furthermore, the functions of the first and second tuner circuits 2 and 3 may well be performed with a single tuner, in which the stationary reception is repeatedly shortly interrupted to
20 allow the tuner during each interruption period to scan through a part of the FM band covering the whole FM band after a number of interruption periods.

THIS PAGE BLANK (USPTO)

4/9 02. 1999
23

4134

(63)

Claims:

1. Method for selecting a tuning frequency for receiving an RF transmitter within an RF frequency band characterized by a band scanning search for detecting transmitters exceeding a predetermined reception quality level, by storing the tuning data thereof and allocating thereto a permanency factor indicating the permanency in reception quality thereof, said tuning frequency being selected on the basis of at least said permanency factor.

2. Method according to claim 1, characterized in that the band scanning search is being repeated in subsequent scan cycles, each detected transmitter increasing respectively decreasing in permanency factor dependent on the detection respectively the absence of detection thereof in subsequent scan cycles.

3. Method according to claim 2, characterized by erasing the tuning data of transmitters having a permanency factor decreasing below a predetermined permanency threshold level.

4. Method according to one of claims 1 to 3, characterized by an RF transmitter being selected from detected transmitters carrying audio programs belonging to a predetermined PTY category.

5. Method according to one of claims 1 to 3, characterized by an RF transmitter being selected from detected FM transmitters carrying traffic messages on the basis of fieldstrength in addition to the permanency factor.

6. FM receiver comprising first and second tuner circuits respectively for receiving a first FM transmitter and for detecting in an FM band FM transmitters received with a reception quality exceeding a predetermined quality threshold level, and storage means for storing the tuning data of the so

detected FM transmitters, the first tuner circuit switching over from an actually received first FM transmitter to a second FM transmitter selected from the detected FM transmitters when the reception quality of the first FM transmitter decreases below a predetermined level, characterized by a processing unit allocating to each detected FM transmitter a permanency factor indicating the permanency in reception quality thereof, said selection of the second FM transmitter being based on at least said permanency factor.

7 FM receiver according to claim 6, characterized by tuning control means varying the tuning of the second tuner circuit to repeat the band scanning search in subsequent scan cycles, the processing unit increasing, respectively decreasing, stepwise the permanency factor of a transmitter at each detection, respectively in the absence of detection, thereof in a subsequent scan cycle.

8 FM receiver according to claim 7, characterized in that the storage locations of tuning data relating to transmitters decreasing in permanency factor below a predetermined permanency threshold level, being released for storage of other transmitter data.

9 FM receiver according to one of claims 6 to 8 capable of receiving RDS signals, characterized in that in selecting the second FM transmitter the processing unit continuously monitors the permanency factor of the FM transmitters carrying an audio program in the same PTY category as the audio program of the first FM transmitter.

10. FM receiver according to claim 6 or 8 capable of receiving RDS signals, characterized in that the processing unit operates to monitor the permanency factor of FM transmitters carrying traffic message information as well as the field strength thereof, the

second FM transmitter being selected from the detected FM transmitters upon receiving a traffic announcement signal on the basis of fieldstrength in addition to the permanency factor.

THIS PAGE BLANK (USPTO)

(63)

Abstract

Method for tuning the reception of radio broadcast signals to an FM RDS transmitter using program related data and transmitter related data and receiver executing the method, providing a band scanning search for detecting FM RDS transmitters exceeding a predetermined reception quality level. To enhance efficiency in data processing and use of storage capacity, transmitter related data including tuning data is stored separately from program related RDS data. Per each detected transmitter a permanency factor indicating the permanency in reception quality thereof is being allocated to each detected RDS transmitter and stored in a first memory bank, along with the relevant tuning data. Per each program identification code carried in the RDS data of the so detected transmitters program related FM RDS data are being stored in a second memorybank, a linkage code defining the storage address within the second memory bank containing the program data carried by the relevant FM RDS transmitter being allocated to the transmitter data of each FM RDS transmitter and stored in the first memory bank.

Figure 1

THIS PAGE BLANK (USPTO)

1 / 3

26. 05. 1999

(70)




Fig. 1

2 / 3

RDS freq 0 (87.5 MHz)		RDS freq 205 (108.0 MHz)	
T...		T...	
T1		T2	
f1 p1:1 NW:0 s1:16 PI=0, PTV=0, TA=0, TMC=0, PS="" PS_MASK		f2 p2:3 NW:1 s2:14 PI=841C PTV=0, TA=0, TMC=0, PS="BRAB/ZO" PS_MASK	
		fx px:1 NW:1 sy:16 PI=8301, PTV=2, TA=1, TMC=0, PS="Radio 3" PS_MASK	
		fy py:2 NW:1 sy:12 PI=8301, PTV=2, TA=1, TMC=0, PS="Radio 3" PS_MASK	

Fig. 2

EPO - DG 1

3 / 3

26. 05. 1999




Fig. 3

THIS PAGE BLANK (USPTO)